



## LED TUBE LT8G - 9/18W

LED tube, G13 base

### Application

Energy efficient LED lamp solutions

### Design Specifications

- Fits new T8 LED fixtures or retrofit T8 fluorescent fixtures (Magnetic Ballast)
- Traditional full glass body construction, G13 lamp base
- High efficiency SMD LED chips, beam 320 degree
- Integral non-dimmable LED driver, 9 or 18 watt models
- Colour temperature 3000K / 4000K / 6000K, CRI >80
- No flicker, instant start, Safety LED fuse included, TYPE A classified product, double insulation



### Technical Specification

Model No.	Description	Input Voltage (V/AC)	Power (W)	Lumens (lm)	CCT (K)	CRI
LT8G60WW	T8 LED 600mm WARM WHITE W/FUSE	240	9	900	3000	80
LT8G60CW	T8 LED 600 mm COOLWHITE W/FUSE	240	9	950	4000	80
LT8G60DL	T8 LED 600 mm DAYLIGHT W/FUSE	240	9	1000	6000	80
LT8G120WW	T8 LED 1200mm WARM W/FUSE	240	18	1800	3000	80
LT8G120CW	T8 LED 1200mm COOL WHITE W/FUSE	240	18	1900	4000	80
LT8G120DL	T8 LED 1200mm DAY LIGHT W/FUSE	240	18	2000	6000	80



## Technical Specification

Model No.	Beam Angle (°)	Dimmable	Diameter (mm)	Length (mm)	Base Type
LT8G60WW	320	NO	25	600	G13
LT8G60CW	320	NO	25	600	G13
LT8G60DL	320	NO	25	600	G13
LT8G120WW	320	NO	25	1200	G13
LT8G120CW	320	NO	25	1200	G13
LT8G120DL	320	NO	25	1200	G13

**Warning:** The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the orientation of the lamp ACTIVE supply.

Due to continued product and technology enhancements, data sourced from sal.net.au shall not form part of any contract and or technical performance guarantee unless expressly confirmed in writing by SAL at the time of order. Products are sold in accordance with [SAL Terms and Conditions of sale](#) and all images shown are for illustration purposes only and may vary from the actual colour or finish. Unless specifically stated, all IP ratings nominated for Interior products are from "below the ceiling".

## Dimensions

### WARNING:

The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the lamp orientation to the ACTIVE supply.



## Product Images

---

**WARNING:**

The luminaire that these LED tubes are installed in may need to be converted in accordance with AS/NZS60598.2.1:2014 by a suitably qualified person. In all instances any electronic components (i.e. driver, electronic ballast, capacitor) must be removed from the circuit. Refer installation instructions for more details, in particular the lamp orientation to the ACTIVE supply.