







## **FEATURES**

- ★ Input voltage: 12V AC/DC
- ★ Wattage: 5W
- ★ Power factor: 0.7
- ★ Life time: 30,000hrs
- ★ Cool running temperature
- ★ IP20
- ★ Not suitable for dimming
- ★ 3 year replacement warranty

## **TECHNICAL DATA**

CODE	DESCRIPTION	KELVIN	LUMENS	CRI	WATT
MR165W	5W MR16 LED WW	3000K	380LM	80	5
MR165N	5W MR16 LED NW	5000K	400LM	80	5

## **RECOMMENDED TRANSFORMER/DRIVER**

BRAND	ITEM NO.	ТҮРЕ	MIN/MAX QTY OF LAMPS	
POSSUM	V99 89400035	TRANSFORMER	5-14PCS	
CLA	CLAPANTHER 20-60W	TRANSFORMER	4-12PCS	
CLA	CLADR12WFP	TRANSFORMER	2-3PCS	
LUXMAN	EDL 10.350.04	LED DRIVER	1-2PCS	
LUXMAN	ETH 50.302	TRANSFORMER	2-10PCS	
LUXMAN	EDL 12.700.02	LED DRIVER	1-3PCS	
CLA	OTTER1	LED DRIVER	2-3PCS	
CLA	CLADRAGONFP	TRANSFORMER	4-12PCS	
LUXMAN	EDL 12.700.04	LED DRIVER	1-3PCS	
CLA	CLA111011	LED DRIVER	1PC ONLY	
CLA	CLA113011	LED DRIVER	5PCS ONLY	
CLA	CLA115011	LED DRIVER	8-9PCS	
CLA	CLA1110011	LED DRIVER	15-18PCS	
CLA	CLA1115011	LED DRIVER	24-27PCS	
CLA	CLA1120011	LED DRIVER	32-36PCS	
N/M	IRON CORE	transformer	1PC+	

UPDATED ON 18/06/2015

Tel: (02) 9938 7100 | Fax: (02) 9938 7115 | Email: sales@clalighting.com.au Website: www.clalighting.com.au

Follow us: facebook.com/CLALighting

## **CLA LIGHTING**