





SMART WiFi PIR SENSOR SERIES II

Get real time alerts or automate other Smart devices when triggered.




Get real time alerts or automate other Smart devices when triggered.

- Create rules and automations based on the conditions.
- Sends alerts to your phone when motion is detected.
- Set time thresholds so that alerts are only received during certain hours of the day.
- Compatible with BrilliantSmart devices via automation & IFTTT.
- Works with other BrilliantSmart devices via automation.

APPLICATIONS

- Create schedules to automate your home.
- Create in app automation, to work with other BrilliantSmart products based on certain behaviours, ie: when movement is detected via a sensor, turn on BrilliantSmart lights, when there is no motion the lights turn off.





SMART WiFi PIR SENSOR SERIES II

TECHNICAL SPECIFICATIONS

Operating Voltage:	DC 4.5V (3 x 1.5V AAA Batteries)
Operating Temperature:	0~40°C
Operating Humidity:	20%-85% RH
Standby Time:	Up to 6 Mths (subject to local conditions)
Detection Area:	5M
Detection Angle:	120°
Weather Rating:	IP20 (Indoor Use only)
Security:	Mac Encryption; WEP/WAPI/TKIP/AES
WiFi Standard:	IEEE802.11/b/g/n
System Req's:	iOS 8.0 or higher, Android 5 or higher.
Warranty:	1 year replacement



	MODEL	COLOUR	DESCRIPTION	BOX SIZE	GROSS WEIGHT	BOX QTY	BARCODE/TUN
RETAIL BOX	22169/05	White	Smart WiFi PIR Sensor Series II	W85 x H85 x D38 mm	0.1 kg	1 pc	 9 312641 221692 >
OUTER CTN	22169/05	White	Smart WiFi PIR Sensor Series II	W350 x H175 x D365 mm	12.5 kg	100 pcs	 19312641221699